



Specifications Ledvance HQL LED P  
E40 32.4W 6000lm D - 840 Cool White |  
Replaces 125W



[View Product](#)

## General Information

|                          |   |
|--------------------------|---|
| SKU                      | 254895                                  |
| EAN                      | 4099854470080                           |
| Brand                    | Ledvance                                |
| Manufacturer Name        | HQL LED FIL P 6000LM 32.4W 840 E40 LEDV |
| Full box quantity        | 1                                       |
| Any Lamp all-in warranty | 5 Years                                 |
| Energy efficiency class  | B                                       |
| Average Lifetime (h)     | 60000                                   |

## Technical Information

|                             |                 |
|-----------------------------|-----------------|
| Technology                  | LED             |
| Product Type Category       | E40 LED         |
| Voltage (V)                 | 220-240         |
| Dimmable                    | Not Dimmable    |
| Cap / Base                  | E40             |
| Colour Code                 | 840 Cool White  |
| Colour temperature (Kelvin) | 4000 Cool White |
| Colour Rendering (Ra)       | 80-89           |
| Colour of Light             | White           |
| Light colour options        | Single Color    |

|                          |           |
|--------------------------|-----------|
| Luminous Efficacy (lm/W) | 185       |
| Power factor             | >0.90     |
| Type of sensor           | No Sensor |

## Lamp Information

|              |         |
|--------------|---------|
| Bulb finish  | Frosted |
| LED Filament | Yes     |

## Dimensions

|               |            |
|---------------|------------|
| Height (mm)   | 214        |
| Diameter (mm) | 90         |
| Shape         | Elliptical |

## Why Any-lamp?

 Order from the **largest lighting specialist** in Europe  **Customised** quotation

 Up to **7 years warranty**  **Easy** return process